

# 300W No-Load Transformer

## SPECIFICATIONS & TECHNICAL DATA

The EmeryAllen 300W No-Load Transformer works with both halogen and LED AC loads. This transformer is dimmable and available with special dimming features.

<b>Model</b>	EA-300W-EPS-LED
<b>Max Wattage</b>	300W
<b>Input Voltage</b>	120V AC
<b>Output Voltage</b>	12V AC
<b>Power Factor</b>	>98%
<b>Protection</b>	Input / Output
<b>Max Temperature</b>	90° C
<b>UL Rating</b>	Damp Location
<b>Class Type</b>	Class 2
<b>IP Rating</b>	IP 60
<b>Load Type</b>	AC LED Bulbs
<b>Standard Dimming</b>	ELV Dimming
<b>Warranty</b>	3 years*

### Features:

- No-Load Transformer
- Auto-Reset, short circuit, overload and thermal protection
- Soft Start
- Low profile compact design which will fit most enclosures
- UL recognized/listed Class 2 power supply which meets UL 2108 requirements
- Isolated output power per NEC and UL safety requirements

